Calhoun
Institutional Archive of the Naval Postgraduate School

Calhoun: The NPS Institutional Archive

DSpace Repository

Theses and Dissertations | 1. Thesis and Dissertation Collection, all items

1972-09

Evaluation of the accuracy of a lower confidence limit estimate for series system reliability.

Evans, Samuel Hall.

Monterey, California. Naval Postgraduate School

http://hdl.handle.net/10945/16114

This publication is a work of the U.S. Government as defined in Title 17, United States Code, Section 101. Copyright protection is not available for this work in the United States.

Downloaded from NPS Archive: Calhoun

DUDLEY KNOX LIBRARY

http://www.nps.edu/library

Calhoun is the Naval Postgraduate School's public access digital repository for research materials and institutional publications created by the NPS community. Calhoun is named for Professor of Mathematics Guy K. Calhoun, NPS's first appointed -- and published -- scholarly author.

Dudley Knox Library / Naval Postgraduate School
411 Dyer Road / 1 University Circle
Monterey, California USA 93943

EVALUATION OF THE ACCURACY
OF A LOWER CONFIDENCE LIMIT ESTIMATE
FOR SERIES SYSTEM RELIABILITY

Samuel Hall Evans

NAVAL POSTGRADUATE SCHOOL
Monterey, California

THESIS

EVALUATION OF THE ACCURACY OF A LOWER CONFIDENCE LIMIT ESTIMATE FOR SERIES SYSTEM RELIABILITY

by

Samuel Hall Evans

Thesis Advisor: W. M. Woods

September 1972

T149915

Approved for public release; distribution unlimited.

NAVAL POSTGRADUATE SCHOOL
MONTEREY, CALIF. 93940

Evaluation of the Accuracy of a Lower Confidence Limit Estimate for Series System Reliability

by

Samuel Hall Evans
Lieutenant, United States Navy
B.S.E.E., University of Texas, 1966

Submitted in partial fulfillment of the
requirements for the degree of

MASTER OF SCIENCE IN OPERATIONS RESEARCH

from the

NAVAL POSTGRADUATE SCHOOL
September 1972

[illegible]

ARY
POSTGRADUATE SCHOOL
NTEREY, CALIF. 93940

ABSTRACT

The purpose of this study is to evaluate the accuracy of a procedure used to compute an estimate of the lower $100(1-\gamma)\%$ confidence limit for reliability of a system of independent components connected in logical series. The procedure takes a Bayesian approach and uses test data on the individual components where the sample sizes may be unequal and no knowledge of the component failure distribution is needed. A computer simulation is used to generate test failure data and to compute estimates for the lower $100(1-\gamma)\%$ confidence limit on system reliability.

TABLE OF CONTENTS

I. INTRODUCTION-- 4

II. RELIABILITY MODEL AND COMPUTATION PROCEDURES---- 5

A. THE RELIABILITY MODEL AND COMPUTATION PROCEDURE: METHOD A-------------------------- 5

1. Summary of the Reliability Model-------- 5

2. Description of the Computation Procedure------------------------------- 8

3. Shortcomings of Method A---------------- 9

B. FIRST MODIFICATION TO THE COMPUTATION PROCEDURE: METHOD B-------------------------- 9

C. SECOND MODIFICATION TO THE COMPUTATION PROCEDURE: METHOD C-------------------------- 11

III. SIMULATION PROCEDURE-------------------------------- 13

IV. RESULTS AND CONCLUSIONS---------------------------- 15

COMPUTER PROGRAM--------------------------------------- 34

LIST OF REFERENCES------------------------------------- 42

INITIAL DISTRIBUTION LIST------------------------------ 43

FORM DD 1473--- 44

I. INTRODUCTION

The problem of determining economically a lower $100(1-\gamma)\%$ confidence limit on the system reliability of complex and expensive systems has plagued reliability managers for a long time. In 1968 Joseph Bram of the Center for Naval Analyses developed an approximate procedure to attack this problem for systems of independent components connected in logical series.[1] It is the purpose of this study to test the accuracy of Bram's procedure and to determine the limits of its usefulness, especially in applications involving systems of ten or more components. The accuracy measurements are determined through a computer simulation.

In an effort to demonstrate reliability goals on expensive systems, it is usually not economically feasible to test the entire system many times. Bram takes a Bayesian approach using test data, successes and failures, on individual components or subsystems to obtain an estimate for the lower confidence limit on the overall system reliability. The method assumes that the components are independent, and test sample sizes for the various components may be unequal. No knowledge or assumptions about the components' failure rates is needed for the computation, only the test failure data.

---

[1] Center for Naval Analyses, O.E.G. Research Contribution No. 79, Confidence Limits for System Reliability, by Joseph Bram, 2 February 1968.

II. RELIABILITY MODEL AND COMPUTATION PROCEDURES

A. THE RELIABILITY MODEL AND COMPUTATION PROCEDURE: METHOD A

1. Summary of the Reliability Model

Consider k independent components, as in Figure 1, connect in logical series with respective individual reliabilities $p_1, p_2, \ldots, p_k$. By the product rule for series systems, the actual overall system reliability, R_s, is given by

$$R_s = \prod_{i=1}^{k} p_i \quad .$$



Component reliability:	p_1	p_2	...	p_k
Number of tests:	n_1	n_2	...	n_k
Number of successes:	s_1	s_2	...	s_k

FIGURE 1.

THE SERIES SYSTEM MODEL

In Bram's Bayesian approach to finding an estimate for the lower confidence bound on system reliability, the p_i's, and hence R_s, are considered to be random variables. If the distribution from which the p_i's were sampled were known, a lower confidence bound could be calculated without

testing. Since this distribution is not known however, the Bayesian's assume a prior distribution which when combined with the test data leads to a posterior distribution, hopefully one that is recognizable and from which confidence limits can easily be computed.

By considering the random variable

$$u = - \ln R_s = - \sum_{i=1}^{k} \ln p_i$$

the procedure approximates the density of u by

$$\phi(u) = \frac{\beta^{\alpha+1}}{\alpha!} u^{\alpha} e^{-\beta u}$$

The parameters α and β will be estimated from test data. This density results from having chosen a prior density for p_i which is questionable on the grounds that it is not normalizable (see prameterization of the prior density, Ref. 1) and leads to a posterior which is also not normalizable. The choice of priors causes difficulty in estimating the parameters of $\phi(u)$ when no failures occur on any of the components, and its effects will be investigated later in this study. However, since this is an approximate method, the development can proceed from the assumption that u does in fact possess the above density and that estimates for α and β can be determined.

If a new random variable v is defined where

$$v = 2\beta u ,$$

then v is distributed "chi square" with 2(α+1) degrees of freedom. Then the lower 100(1-γ)% confidence limit, $R_{s,L(\gamma)}$, can be found as follows:

$$P[2\beta u < \chi^2_{2(\alpha+1),1-\gamma}] = 1 - \gamma$$

$$P[u < \frac{\chi^2_{2(\alpha+1),1-\gamma}}{2\beta}] = 1 - \gamma$$

$$P[e^{-u} > \exp(-\frac{\chi^2_{2(\alpha+1),1-\gamma}}{2\beta})] = 1 - \gamma$$

$$P[R_s > \exp(-\frac{\chi^2_{2(\alpha+1),1-\gamma}}{2\beta})] = 1 - \gamma$$

From the probability statement above,

$$R_{s,L(\gamma)} = \exp(-\frac{\chi^2_{2(\alpha+1),1-\gamma}}{2\beta})$$

is the desired approximate lower confidence limit. The problem is to find an estimate, $\hat{R}_{s,L(\gamma)}$, for $R_{s,L(\gamma)}$ which will yield values sufficiently accurate for the reliability manager's purposes. Bram's method specifies estimates $\hat{\alpha}$ and $\hat{\beta}$, which are computed from the test data, and substituted into the above expression, to obtain

$$\hat{R}_{s,L(\gamma)} = \exp(-\frac{\chi^2_{2(\hat{\alpha}+1),1-\gamma}}{2\hat{\beta}}) .$$

In the following section Bram's computation procedure for $\hat{\alpha}$ and $\hat{\beta}$ is described.

2. Description of the Computation Procedure

In the following, Bram's procedure for computing $\hat{R}_{s,L(\gamma)}$, will be referred to as method A, and the author's modifications to the original procedure will be referred to as methods B and C.

For descriptive purposes, after testing has been done, consider the k system components to be arranged as follows: 1, 2,..., k_1, k_1+1,..., k, where components 1, ..., k_1 are those which experience no failures, and k_1+1, ..., k are those which experience one or more failures. Let n_i be the number of tests on component i and s_i be the number of successes in the n_i tests. To get $\hat{R}_{s,L(\gamma)}$ by method A proceed as follows:

$$\hat{M}_A = \sum_{i=k_1+1}^{k} \sum_{j=s_i}^{n_i-1} \frac{1}{j} ,$$

$$\hat{V}_A = \sum_{i=k_1+1}^{k} \sum_{j=s_i}^{n_i-1} \frac{1}{j^2} ,$$

$$\hat{\alpha} = \frac{\hat{M}_A^2}{\hat{V}_A} - 1 \quad \text{and} \quad \hat{\beta} = \frac{\hat{M}_A}{\hat{V}_A} , \quad \text{and}$$

$$\hat{R}_{s,L(\gamma)} = \exp\left(- \frac{\chi^2_{2(\hat{\alpha}+1),1-\gamma}}{2\hat{\beta}}\right)$$

$\hat{M}_A$ and $\hat{V}_A$ are estimates of the mean and variance of u under method A. In cases where $(\hat{\alpha}+1)$ is non-integer, interpolation is to be used.

3. Shortcomings of Method A

It should be noted that the double sums do not account for components which experience no failures in testing, and if none of the system's components fails, $\hat{\alpha}$ and $\hat{\beta}$ are not defined: under these circumstances the procedure can not be used as it stands. Herein lies the major obstacle to application of the procedure to highly reliable system testing programs where it is quite possible that no failures will occur. In testing the accuracy of method A, whenever no failures occur, $\hat{R}_{s,L(\gamma)}$ is set equal to unity by the author's choice, since Bram makes no allowance for this possibility.

Secondly, as $\hat{\alpha}$ is defined, it is possible that $2(\hat{\alpha}+1)$, the estimate of the degrees of freedom of the chi square random variable can be less than one. Since a chi square variate must have at least one degree of freedom, some provision must be made to account for this inconsistency. For computation purposes in testing the original procedure of method A and the modifications, whenever $2(\hat{\alpha}+1)$ is less than one, the degrees of freedom are set equal to one by the author's choice. For all fractional values of $2(\hat{\alpha}+1)$ greater than one, linear interpolation between the tabulated integer degrees of freedom are used, as specified in the original procedure.

B. FIRST MODIFICATION TO THE COMPUTATION PROCEDURE: METHOD B

The only way that the true lower confidence limit $R_{s,L(\gamma)}$ can be unity is to have no failures on an infinite number of

tests; this would be impossible to demonstrate. In searching for a more realistic value for $\hat{R}_{s,L(\gamma)}$ when no failures occur, one might be led to believe that $\hat{R}_{s,L(\gamma)}$ should be close to but not equal to one. Due to its discrete character, the procedure of method A will compute one value of $\hat{R}_{s,L(\gamma)}$ which is closest to unity; this will happen when one failure occurs on the component with the greatest number of tests. An approximation of a more accurate estimate of $\hat{R}_{s,L(\gamma)}$ when no failures occur, can be obtained by using one half the original estimates $\hat{M}_A$ and $\hat{V}_A$, where one failure occurs on the component with the most tests. This has the effect of considering a partial failure on the component with the most tests and tends to smooth the discrete distribution of values of $\hat{R}_{s,L(\gamma)}$ near unity.

In summary, computations under method B proceed as follows:

$$\begin{aligned} \hat{M}_B &= \hat{M}_A \\ \hat{V}_B &= \hat{V}_A \end{aligned} \qquad \text{if } k_1 < k, \quad \text{and}$$

$$\left.\begin{aligned} \hat{M}_B &= \frac{1}{2(N_{max} - 1)} \\ \hat{V}_B &= \frac{1}{2(N_{max} - 1)^2} \end{aligned}\right\} \qquad \text{if } k_1 = k.$$

N_{max} is the number of tests on the component with the greatest number of tests.

$$\hat{\alpha} = \frac{\hat{M}_B^2}{\hat{V}_B} - 1 \quad ,$$

$$\hat{\beta} = \frac{\hat{M}_B}{\hat{V}_B} \quad , \quad \text{and}$$

$$\hat{R}_{s,L(\gamma)} = \exp[- \frac{\chi^2_{2(\hat{\alpha}+1),1-\gamma)}}{2\hat{\beta}}]$$

If $2(\hat{\alpha}+1) < 1.0$, then set $2(\hat{\alpha}+1) = 1.0$.

C. SECOND MODIFICATION TO THE COMPUTATION PROCEDURE: METHOD C

In an effort to refine method B so that it might be useful under conditions of very high component reliability and small amounts of testing, a second modification is presented. Method C of computing $\hat{M}$ and $\hat{V}$ is an attempt to further smooth the distribution of $\hat{R}_{s,L(\gamma)}$ and has the effect of adding a partial failure to each component which experiences no failure during testing. For method C computation proceeds as follows:

$$\hat{M}_C = \sum_{i=1}^{k_1} \frac{1}{2\ k_1^2\ (n_i - 1)} + \hat{M}_A$$

$$\hat{V}_C = \sum_{i=1}^{k_1} \frac{1}{2\ k_1^2\ (n_i - 1)^2} + \hat{V}_A$$

$$\hat{\alpha} = \frac{\hat{M}_C^2}{\hat{V}_C} - 1 \quad ,$$

$$\hat{\beta} = \frac{\hat{M}_C}{\hat{V}_C} \quad , \text{ and}$$

$$\hat{R}_{s,L(\gamma)} = \exp[- \frac{\chi^2_{2(\hat{\alpha}+1),1-\gamma}}{2\hat{\beta}}]$$

Again, if $2(\hat{\alpha}+1) < 1.0$, set $2(\hat{\alpha}+1) = 1.0$.

From these computations it is seen that if every component experiences at least one failure, i.e. $k_1 = 0$, then method C reduces to method B. On the other hand, if a system consists of say forty components, and there is limited testing relative to the component unreliability of say ten of the components, one might feel that some adjustment should be made to the overall estimate $\hat{R}_{s,L(\gamma)}$ to account for the lack of testing on those ten components; that is the motivation for this second modification. Furthermore, any method of computing $\hat{R}_{s,L(\gamma)}$ which yields accurate results with less testing than another method will be more desirable economically.

III. SIMULATION PROCEDURE

The purpose of the computer simulation in this study is to demonstrate the accuracy of the procedures described in section II. The simulation considers the system of k components of Figure 1, where the component reliabilities and hence R_s are assumed to be known. For this system tests are simulated by the Monte Carlo technique, generating failure data which is used to compute $\hat{R}_{s,L(\gamma)}$ by each of the three methods A, B, and C. By replicating the procedure 1000 times, 1000 values of $\hat{R}_{s,L(\gamma)}$ are generated which are then arranged in ascending order. If the method of computing $\hat{R}_{s,L(\gamma)}$ is accurate, then $100(1-\gamma)\%$ of the time the true system reliability, R_s, will be greater than or equal to $\hat{R}_{s,L(\gamma)}$. Therefore the $100(1-\gamma)^{th}$ percentile point of the 1000 ordered values of $\hat{R}_{s,L(\gamma)}$, $A_{1-\gamma}$, should be equal to or very close to the value of R_s if the method is accurate. For example, if $\gamma = .10$ then the 90^{th} percentile point or 900^{th} ordered value of $\hat{R}_{s,L(\gamma)}$ should be close to R_s. It is this difference, $|R_s - A_{1-\gamma}|$, that is the primary measure of accuracy of the method of estimation. Another measure of the accuracy is the true level of confidence. The true level of confidence is found by determining the percentage of the values of $\hat{R}_{s,L(\gamma)}$ that are less than or equal to R_s. If the method is accurate the true level of confidence will be very close to $100(1-\gamma)\%$.

One of the main concerns of this study is to determine what minimum amount of testing is necessary to insure that the method will provide accurate results. This minimum amount of testing will be different for each system and will be dependent on the number of components and their reliabilities. For this reason the quantity

$$TT = \sum_{i=1}^{k} n_i(1-p_i)$$

is used as a measure of the amount of testing relative to the system reliability.[2] Low values of TT occur when combinations of high reliability and small numbers of tests occur, and TT increases directly with the number of tests per component and inversely with component reliability. Intuitively one would feel that as TT decreases the accuracy of the computation procedure will decrease since fewer failures will occur, and less information will be obtained. One purpose of the simulation is to determine for what values of TT the various methods meet desired accuracy goals.

---

[2] Borsting, Jack R., and Woods, W. Max, A Method for Computing Lower Confidence Limits on System Reliability Using Component Failure Data With Unequal Sample Sizes, Naval Postgraduate School, Monterey, California, June 1968.

IV. RESULTS AND CONCLUSIONS

The analysis of accuracy results are shown in Tables I and II. The cases considered are grouped according to the number of components, system reliability, and value of TT. The component reliabilities, p_i's, are held constant in some cases while the number of tests per component, n_i's, are varied, to yield a range of TT values. In other cases the n_i's are fixed and the p_i's varied. Twenty-three cases of systems with reliabilities ranging from approximately .87 to .95 and consisting of 10, 20, and 40 components are considered.

As expected the tendency of all methods to increase in accuracy as TT increases is substantiated. In addition, the tendency of increased accuracy from methods A, to B, to C is also substantiated. Cases 21, 22, and 23 show clearly that for TT = 10.0 the accuracy of the three methods is essentially the same for all three methods of computation, since with this relatively high amount of testing the methods become identical. These three cases also show that as the number of system components changes, if R_s and TT are held constant, the accuracy of the three methods remains essentially unchanged.

It is up to the user to determine what accuracy is acceptable when employing any procedure to compute $\hat{R}_{s,L(\gamma)}$. For illustrative purposes, if one considers $|R_s - A_{1-\gamma}| < .02$ to be acceptable accuracy, then for a 40 component system

with an overall reliability of approximately .90, the testing program should be such that TT = 6.50 is a minimum and TT > 9.0 would be desirable. As TT decreases below 6.50 there is a marked deterioration in accuracy of all three methods as measured by both $|R_s - A_{1-\gamma}|$ and the true level of confidence versus the desired level of confidence. Another key factor to consider in using any of these methods is that each is sensitive to the individual component test sample size, n_i. If n_i is quite small, say less than 10, for any component regardless of TT, a failure on one of those n_i tests will tend to have a disproportionate effect on $\hat{R}_{s,L(\gamma)}$. Note that in cases 6 through 10 accuracy proves to be not as good as in cases 1 through 5 for k = 20 and corresponding values of TT. This is because the n_i values are generally lower for cases 6 through 10 and in some cases n_i is less than 10.

The results show little difference in accuracy between the 80% ($\gamma = .20$) and 90% ($\gamma = .10$) confidence levels among the various cases and methods. There is no general tendency for the accuracy to be better at either level although one might expect that accuracy at the 80% confidence level would be better than at the 90% level. For example in case 14A (TT = 6.55) accuracy is better at the 90% level, but in cases 13A (TT = 4.05) and 15A (TT = 9.10) accuracy is better at the 80% level.

These methods are approximations. No analytical justification is given for the modifications suggested. Intuition

has been the guiding factor in development of the methods and the accuracy tests which are based on sound analytical techniques are the basis of acceptance or rejection of the method as a useful tool. Since systems vary widely in their composition, it is not possible to cover them all with a set of specific rules as to when it would be appropriate to use one of the methods for computing $\hat{R}_{s,L(\gamma)}$. However, from these results two general rules follow:

1. For systems of ten to forty independent components TT greater than 10.0 should yield accuracies of $|R_s - A_{1-\gamma}| < .01$ provided that,
2. no component is tested less than 10 times, i.e. $n_i \geq 10$ for all components.

If these two rules are followed it can also be concluded that method B should be employed since there should be no appreciable difference in the accuracies of methods A, B, and C, and B is easier to compute than C. Also B does not suffer from the possibility, remote as it would be if TT were greater than 10.0, of yielding $\hat{R}_{s,L(\gamma)} = 1.0$ as would method A. Any system under consideration can be tested using using the computer simulation procedure, and as TT decreases below 10.0, either because of economic or time constraints in the testing program, this would be recommended.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
1A	20	$n_i=16$, $i=1,\ldots,5$; $n_i=20$, $i=6,\ldots,10$; $n_i=40$, $i=11,\ldots,20$; $p_i=.9975$, $i=1,\ldots,20$.	1.45	.9512	.10 .20	1.0000 1.0000	.0488 .0488	.770 .563
1B	20	"	1.45	.9512	.10 .20	.9659 .9792	.0147 .0280	NC* NC
1C	20	"	1.45	.9512	.10 .20	.9402 .9598	.0110 .0088	1.000 NC
2A	20	$n_i=6$, $i=1,\ldots,5$; $n_i=30$, $i=6,\ldots,10$; $n_i=100$, $i=11,\ldots,20$. $p_i=.9975$, $i=1,\ldots,20$.	2.95	.9512	.10 .20	.9770 .9702	.0258 .0190	.668 .514
2B	20	"	2.95	.9512	.10 .20	NC NC	NC NC	NC NC
2C	20	"	2.95	.9512	.10 .20	.9566 .9650	.0054 .0138	.869 .563

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
3A	20	$n_i=14$, $i=1,\ldots,5$; $n_i=60$, $i=6,\ldots,10$; $n_i=125$, $i=1,\ldots,20$; $p_i=.9975$, $i=1,\ldots,20$.	4.05	.9512	.10 .20	.9691 .9660	.0179 .0148	.714 .590
3B	20	"	4.05	.9512	.10 .20	NC NC	NC NC	NC NC
3C	20	"	4.05	.9512	.10 .20	.9659 .9641	.0147 .0129	.756 NC
4A	20	$n_i=24$, $i=1,\ldots,5$; $n_i=100$, $i=6,\ldots,10$; $n_i=200$, $i=11,\ldots,20$; $p_i=.9975$, $i=1,\ldots,20$.	6.55	.9512	.10 .20	.9669 .9608	.0157 .0096	.708 .618
4B	20	"	6.55	.9512	.10 .20	NC NC	NC NC	NC NC
4C	20	"	6.55	.9512	.10 .20	.9627 .9600	.0115 .0088	.765 NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma} \rvert$	TRUE CONF. LEVEL
5 A	20	n_i=28 , i=1,...,5; n_i=100, i=6,...,10; n_i=300, i=11,...,20; p_i=.9975, i = 1,...,20.	9.10	.9512	.10	.9650	.0138	.729
					.20	.9627	.0115	.622
5 B	20	"	9.10	.9512	.10	NC	NC	NC
					.20	NC	NC	NC
5 C	20	"	9.10	.9512	.10	.9635	.0123	.730
					.20	.9671	.0159	.673
6 A	20	n_i=8 , i=1,...,5; n_i=10, i=6,...,10; n_i=20, i=11,...,20; p_i=.995, i=1,...,20.	1.45	.9046	.10	1.0000	.0954	.773
					.20	1.0000	.0954	.521
6 B	20	"	1.45	.9046	.10	.9312	.0266	NC
					.20	.9578	.0532	NC
6 C	20	"	1.45	.9046	.10	.8808	.0238	NC
					.20	.9163	.0117	NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
7A	20	$n_i=3$, $i=1,\ldots,5$; $n_i=15$, $i=6,\ldots,10$; $n_i=50$, $i=11,\ldots,20$; $p_i=.995$, $i=1,\ldots,20$.	2.95	.9046	.10 .20	.9541 .9406	.0495 .0360	.638 .528
7 B	20	"	2.95	.9046	.10 .20	NC NC	NC NC	NC NC
7 C	20	"	2.95	.9046	.10 .20	.8946 .9289	.0100 .0243	NC .719
8 A	20	$n_i=7$, $i=1,\ldots,5$; $n_i=35$, $i=6,\ldots,10$; $n_i=60$, $i=11,\ldots,20$; $p_i=.995$, $i=1,\ldots,20$.	4.05	.9046	.10 .20	.9362 .9324	.0316 .0278	.697 .575
8 B	20	"	4.05	.9046	.10 .20	NC NC	NC NC	NC NC
8 C	20	"	4.05	.9046	.10 .20	.9295 .9259	.0249 .0213	.713 .588

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
9A	20	$n_i=12$, $i=1,\ldots,5$; $n_i=50$, $i=6,\ldots,10$; $n_i=100$, $i=11,\ldots,20$; $p_i=.995$, $i=1,\ldots,20$.	6.55	.9046	.10 .20	.9346 .9292	.0300 .0246	.711 .618
9B	20	"	6.55	.9046	.10 .20	NC NC	NC NC	NC NC
9C	20	"	6.55	.9046	.10 .20	.9312 .9275	.0266 .0229	.749 .619
10A	20	$n_i=14$, $i=1,\ldots,5$; $n_i=50$, $i=6,\ldots,10$; $n_i=150$, $i=11,\ldots,20$; $p_i=.995$, $i=1,\ldots,20$.	9.10	.9046	.10 .20	.9315 .9261	.0269 .0215	.723 .624
10B	20	"	9.10	.9046	.10 .20	NC NC	NC NC	NC NC
10C	20	"	9.10	.9046	.10 .20	.9283 .9227	.0237 .0181	.726 .646

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma} \rvert$	TRUE CONF. LEVEL
11A	40	$n_i=5$, $i=1,\dots,15$; $n_i=10$, $i=16,\dots,30$; $n_i=50$, $i=31,\dots,40$; $p_i=.998$, $i=1,\dots,40$.	1.45	.9230	.10	1.0000	.0770	.419
					.20	.9677	.0447	.410
11 B	40	"	1.45	.9230	.10	.9727	.0497	NC
					.20	NC	NC	NC
11 C	40	"	1.45	.9230	.10	.9450	.0220	.772
					.20	.9644	.0414	.610
12A	40	$n_i=5$, $i=1,\dots,15$; $n_i=10$, $i=16,\dots,30$; $n_i=100$, $i=31,\dots,35$; $n_i=150$, $i=36,\dots,40$; $p_i=.998$, $i=1,\dots,40$.	2.95	.9230	.10	.9847	.0617	.404
					.20	.9801	.0571	.378
12B	40	"	2.95	.9230	.10	NC	NC	NC
					.20	NC	NC	NC
12C	40	"	2.95	.9230	.10	.9539	.0309	.495
					.20	.9650	.0420	.429

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
13A	40	$n_i=5, i=1,\ldots 5$; $n_i=10, i=6,\ldots,10$; $n_i=20, i=11,\ldots,20$; $n_i=50, i=21,\ldots,30$; $n_i=100, i=31,\ldots,35$; $n_i=150, i=36,\ldots,40$; $p_i=.998$, $i=1,\ldots,40$.	4.05	.9230	.10 .20	.9650 .9548	.0420 .0318	.649 .570
13B	40	"	4.05	.9230	.10 .20	NC NC	NC NC	NC NC
13C	40	"	4.05	.9230	.10 .20	.9524 .9525	.0294 .0295	.701 .594
14 A	40	$n_i=5, i=1,\ldots,5$; $n_i=50, i=6,\ldots,20$; $n_i=100$, $i=21,\ldots,30$; $n_i=150$, $i=31,\ldots,40$; $p_i=.998$, $i=1,\ldots,40$.	6.55	.9230	.10 .20	.9396 .9428	.0166 .0198	.785 .625
14 B	40	"	6.55	.9230	.10 .20	NC NC	NC NC	NC NC
14 C	40	"	6.55	.9230	.10 .20	.9356 .9381	.0126 .0151	.825 .639

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma} \rvert$	TRUE CONF. LEVEL
15A	40	n_i= 50, i=1,...,10; n_i=100, i=11,...,20; n_i=150, i=21,...,40; p_i=.998, i=1,...,40.	9.00	.9230	.10	.9294	.0064	.861
					.20	.9282	.0052	.757
15B	40	"	9.00	.9230	.10	NC	NC	NC
					.20	NC	NC	NC
15C	40	"	9.00	.9230	.10	.9292	.0062	.863
					.20	.9280	.0050	NC
16A	40	n_i=15, i=1,...,40 p_i=.999,i=1,...,5;p_i=.998,i=6,...,20 p_i=.997, i=21,...,35; p_i=.990, i=36,...,40.	1.95	.8778	.10	1.0000	.1222	.851
					.20	.8914	.0136	.574
16B	40	"	1.95	.8778	.10	.9078	.0300	NC
					.20	NC	NC	NC
16C	40	"	1.95	.8778	.10	NC	NC	NC
					.20	.8902	.0124	NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
17 A	40	n_i=20, i=1,...,40; p_i=.999,i=1,...,5;p_i=.998,i=6,...,20; p_i=.997, i=21,...,35; p_i=.990, i=36,...,40.	2.60	.8778	.10	.8858	.0080	.746
					.20	.9188	.0410	.732
17 B	40	"	2.60	.8778	.10	NC	NC	NC
					.20	NC	NC	NC
17 C	40	"	2.60	.8778	.10	.8848	.0070	.735
					.20	.9179	.0401	.754
18A	40	n_i=30, i=1,...,40 p_i=.999,i=1,...,5;p_i=.998,i=6,...,20; p_i=.997,i=21,...,35; p_i=.990,i=36,...,40	3.90	.8778	.10	.9236	.0458	.897
					.20	.9017	.0239	.746
18B	40	"	3.90	.8778	.10	NC	NC	NC
					.20	NC	NC	NC
18C	40	"	3.90	.8778	.10	.9229	.0451	NC
					.20	.9012	.0234	NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma}\rvert$	TRUE CONF. LEVEL
19 A	40	$n_i=50$, $i=1,\dots,40$ $p_i=.999, i=1,\dots,5; p_i=.998, i=6,\dots,20;$ $p_i=.997, i=21,\dots,35;$ $p_i=.990, i=36,\dots,40.$	6.50	.8778	.10	.8975	.0197	.884
					.20	.8722	.0055	.805
19 B	40	"	6.50	.8778	.10	NC	NC	NC
					.20	NC	NC	NC
19 C	40	"	6.50	.8778	.10	.8971	.0193	NC
					.20	.8719	.0059	NC
20 A	40	$n_i=70$, $i=1,\dots,40$ $p_i=.999, i=1,\dots,5; p_i=.998, i=6,\dots,20;$ $p_i=.997, i=21,\dots,35;$ $p_i=.990, i=36,\dots,40.$	9.10	.8778	.10	.8745	.0033	.902
					.20	.8764	.0014	.820
20 B	40	"	9.10	.8778	.10	NC	NC	NC
					.20	NC	NC	NC
20 C	40	"	9.10	.8778	.10	.8743	.0035	NC
					.20	.8762	.0016	NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma} \rvert$	TRUE CONF. LEVEL
21A	10	$n_i=125$, $i=1,\ldots,10$; $p_i=.992$, $i=1,\ldots,10$.	10.0	.9228	.10 .20	.9279 .9290	.0051 .0062	.879 .772
21 B	10	"	10.0	.9228	.10 .20	NC NC	NC NC	NC NC
21 C	10	"	10.0	.9228	.10 .20	.9270 .9280	.0042 .0052	NC NC
22A	20	$n_i=125$, $i=1,\ldots,20$; $p_i=.996$, $i=1,\ldots,20$.	10.0	.9229	.10 .20	.9281 .9290	.0052 .0061	.869 .793
22 B	20	"	10.0	.9229	.10 .20	NC NC	NC NC	NC NC
22 C	20	"	10.0	.9229	.10 .20	.9278 .9281	.0048 .0052	NC NC

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

CASE NO.	K	n_i and p_i	TT	R_s	γ	$A_{1-\gamma}$	$\lvert R_s - A_{1-\gamma} \rvert$	TRUE CONF. LEVEL
23A	40	$n_i=125$, $i=1,\ldots,40$; $p_i=.998$, $i=1,\ldots,40$.	10.0	.9230	.10	.9281	.0051	.885
					.20	.9292	.0062	.779
23B	40	"	10.0	.9230	.10	NC	NC	NC
					.20	NC	NC	NC
23C	40	"	10.0	.9230	.10	.9280	.0050	NC
					.20	.9290	.0060	NC
A								
B								
C								

*NC indicates No Change from corresponding result of previous method.

Summary of Accuracy Results by Case
TABLE I.

Case No.	k	TT	R_s	$\lvert R_s - A_{1-\gamma} \rvert$		
				A	B	C
16	40	1.95	.8778	.1222	.0300	NC
6	20	1.45	.9046	.0954	.0266	.0238
11	40	1.45	.9230	.0770	.0497	.0220
1	20	1.45	.9512	.0488	.0147	.0110
17	40	2.60	.8778	.0080	NC	.0070
7	20	2.95	.9046	.0495	NC	.0100
12	40	2.95	.9230	.0617	NC	.0309
2	20	2.95	.9512	.0258	NC	.0054
18	40	3.90	.8778	.0458	NC	.0451
8	20	4.05	.9046	.0316	NC	.0249
13	40	4.05	.9230	.0420	NC	.0294
3	20	4.05	.9512	.0179	NC	.0147
19	40	6.50	.8778	.0197	NC	.0193
9	20	6.55	.9046	.0300	NC	.0266
14	40	6.55	.9230	.0166	NC	.0126
4	20	6.55	.9512	.0157	NC	.0115

Summary of Accuracy Results for $\gamma = .10$
Table II

Case No.	k	TT	R_s	$\lvert R_s - A_{1-\gamma}\rvert$		
				A	B	C
20	40	9.10	.8778	.0033	NC	.0035
10	20	9.10	.9046	.0269	NC	.0237
15	40	9.00	.9230	.0064	NC	.0062
5	20	9.10	.9512	.0138	NC	.0123
21	10	10.0	.9228	.0051	NC	.0042
22	20	10.0	.9229	.0052	NC	.0048
23	40	10.0	.9230	.0051	NC	.0050

Summary of Accuracy Results for $\gamma = .10$
Table II

Case No.	k	TT	R_s	$\lvert R_s - A_{1-\gamma} \rvert$		
				A	B	C
16	40	1.95	.8778	.0136	NC	.0124
6	20	1.45	.9046	.0954	.0532	.0117
11	40	1.45	.9230	.0447	NC	.0414
1	20	1.45	.9512	.0488	.0280	.0088
17	40	2.60	.8778	.0080	NC	.0070
7	20	2.95	.9046	.0360	NC	.0243
12	40	2.95	.9230	.0571	NC	.0420
2	20	2.95	.9512	.0190	NC	.0138
18	40	3.90	.8778	.0239	NC	.0234
8	20	4.05	.9046	.0278	NC	.0213
13	40	4.05	.9230	.0318	NC	.0295
3	20	4.05	.9512	.0148	NC	.0129
19	40	6.50	.8778	.0055	NC	.0059
9	20	6.55	.9046	.0246	NC	.0229
14	40	6.55	.9230	.0198	NC	.0151
4	20	6.55	.9512	.0096	NC	.0088

Summary of Accuracy Results for $\gamma = .20$
Table II

Case No.	k	TT	R_s	$\lvert R_s - A_{1-\gamma} \rvert$		
				A	B	C
20	40	9.10	.8778	.0014	NC	.0016
10	20	9.10	.9046	.0215	NC	.0181
15	40	9.00	.9230	.0052	NC	.0050
5	20	9.10	.9512	.0115	NC	.0159
21	10	10.0	.9228	.0062	NC	.0052
22	20	10.0	.9229	.0061	NC	.0052
23	40	10.0	.9230	.0062	NC	.0060

Summary of Accuracy Results for $\gamma = .20$
Table II

COMPUTER PROGRAM

```
SIMULATION PROGRAM TO EVALUATE THE ACCURACY OF THE LOWER CONFIDENCE
ESTIMATE FOR SERIES SYSTEM RELIABILITY
COMP0 = METHOD A OF TEXT
COMP1 = METHOD B OF TEXT
COMP2 = METHOD C OF TEXT
      DIMENSION N(50), P(50), NS(50), GAMMA(5)
      DIMENSION NT(50), NST(50), NFT(50)
      DIMENSION A(5), CONF(5),RSLCL(1000)
      DIMENSION NF(50)
      DIMENSION  PCNTIL(5), CSTABL(100,2)
      DATA N/50*0/, P/50*0.0/, NS/50*0/, GAMMA/5*0.0/
      DATA A/5*0.0/, CONF/5*0.0/, RSLCL/1000*0.0/
      DATA NT/50*0/, NST/50*0/, NFT/50*0/
      DATA NF/50*0/
      DATA  PCNTIL/5*0.0/, CSTABL/200*0.0/
      KOUNT = 0
      IOUT = 0
      NF1 = 0
      ISTART = 65549
      IRN = ISTART
      M = 12493
      KK = 8 * M + 3
      ISTOP = 0
      IFLAG0 = 0
      IFLAG1 = 0
      IFLAG2 = 1
      IF (IFLAG0.EQ.0) GO TO 0020
      ICOMP1 = 0
      ICOMP2 = 0
      IFLAG2 = 0
      GO TO 0050
 0020 IF (IFLAG1.EQ.0) GO TO 0030
      ICOMP1 = 1
      ICOMP2 = 0
      GO TO 0050
 0030 IF (IFLAG2.EQ.0) GO TO 0045
      ICOMP1 = 0
      ICOMP2 = 1
      ISTOP = 1
      GO TO 0050
 0045 WRITE (6,0046)
 0046 FORMAT (12X, 'IFLAG VALUES SCREWED UP')
      STOP
READ INPUT DATA
 0050 READ (5,0100) K, NGAMMA, NREP
 0100 FORMAT (3I5)
      READ (5,0200) (GAMMA(J), J= 1, NGAMMA)
 0200 FORMAT (5F10.5)
```

```
      ILOOP = 0                                                         00000470
 0300 ILOOP = ILOOP + 1                                                 00000480
      READ (5,0400) N(ILOOP), P(ILOOP)                                  00000490
 0400 FORMAT (1I5, 1F10.5)                                              00000500
      IF(ILOOP.LT.K) GO TO 0300                                         00000510
      DO 0600 I= 1, 100                                                 00000520
      READ (5,0500) (CSTABL(I,J), J=1,2)                                00000530
 0500 FORMAT (2F10.5)                                                   00000540
 0600 CONTINUE                                                          00000550
      ILOOP = 0                                                         00000560
 0700 ILOOP = ILOOP + 1                                                 00000570
      PCNTIL(ILOOP) = 1.0 - GAMMA(ILOOP)                                00000580
      IF(ILOOP.LT.NGAMMA) GO TO 0700                                    00000590
      NPOI = N(1)                                                       00000600
ECHO CHECK INPUTS                                                       00000610
      IF(NREP.EQ.1000) GO TO 0790                                       00000620
      IF(NREP.EQ.100) GO  TO 0790                                       00000630
      WRITE (6,0780) NREP                                               00000640
 0780 FORMAT(1X,///, 'ERROR, NREP NOT EQUAL TO 1000 OR 100, NREP= 'I10) 00000650
      STOP                                                              00000660
 0790 WRITE (6,0800) K, NGAMMA, NREP                                    00000670
 0800 FORMAT ('1', 7X, 'INPUT VALUES FOR SIMULATION', //,               00000680
     119X, 'K= ', I5, 5X, 'NUMBER OF COMPONENTS IN SERIES',             00000690
     2/, 14X, 'NGAMMA= ', I5, 5X, 'NUMBER OF CONFIDENCE LEVELS',        00000700
     3/, 16X, 'NREP= ', I5, 5X, 'NUMBER OF REPLICATIONS', /)            00000710
      ILOOP = 0                                                         00000720
 0900 ILOOP = ILOOP + 1                                                 00000730
      WRITE (6,1000) ILOOP, GAMMA(ILOOP)                                00000740
 1000 FORMAT (12X, 'GAMMA(', I1, ')= ', F5.3, /)                        00000750
      IF(ILOOP.LT.NGAMMA) GO TO 0900                                    00000760
      WRITE (6, 1100)                                                   00000770
 1100 FORMAT (1X, //, 12X, 'COMPONENT       COMPONENT', 5X,             00000780
     1'NUMBER OF', 7X, 'NUMBER OF', 7X, 'NUMBER OF',/,13X,'NUMBER',7X,  00000790
     2'RELIABILITY   TEST TRIALS   TEST SUCCESSES   TEST FAILURES',//)  00000800
      ILOOP = 0                                                         00000810
 1200 ILOOP = ILOOP + 1                                                 00000820
      WRITE (6,1300) ILOOP, P(ILOOP), N(ILOOP), NS(ILOOP), NF(ILOOP)    00000830
 1300 FORMAT (12X, I5, 12X, F6.4, 9X, I6, 10X, I6, 10X,I6,/)            00000840
      IF(ILOOP.LT.K) GO TO 1200                                         00000850
      WRITE(6,1400) PCNTIL(1), PCNTIL(2)                                00000860
 1400 FORMAT (1X, //, 12X, 'SELECTED PERCENTILES FOR THE ',             00000870
     1'CHI SQUARED DISTRIBUTION', /, 14X, 'PERCENTILE', 1X, F5.2, 4X,   00000880
     2F5.2, /, 18X, 'DF')                                               00000890
      DO 1600 I= 1,100                                                  00000900
      WRITE (6,1500) I, (CSTABL(I,J), J=1,2)                            00000910
 1500 FORMAT (15X, I5,   5X, F6.2, 4X, F6.2)                            00000920
 1600 CONTINUE                                                          00000930
FIND COMPONENT WHICH HAS LARGEST NO. OF TESTS                           00000940
```

```
      K1 = K - 1
      I = 1
 1610 I1 = I + 1
      IF (N(I).GE.N(I1)) GO TO 1620
      NMAX = N(I1)
      GO TO 1630
 1620 NMAX = N(I)
 1630 IF(I.GE.K1) GO TO 1640
      I = I+ 1
      GO TO 1610
 1640 NMAX1 = NMAX - 1
      XNMAX1 = NMAX1
COMPUTE SERIES SYSTEM RELIABILITY BY PRODUCT ASSUMPTION
      RCOMP = 1.0
      ILOOP = 0
 1700 ILOOP = ILOOP + 1
      RCOMP = RCOMP * P(ILOOP)
      IF(ILOOP.LT.K) GO TO 1700
      WRITE (6,1800)
 1800 FORMAT ('1', 7X, 'SIMULATION OUTPUT', //)
COMPUTE TT
      TT = 0.0
      DO 1900 I= 1,K
      T = N(I) * (1.0 - P(I))
      TT = TT + T
 1900 CONTINUE
BEGIN SIMULATION
 1950 L = 1
 2000 G= GAMMA(L)
      J= 1
GENERATE K VALUES OF NS(I) BY SIMULATING TESTS
 2100 I= 1
      II= 1
 2200 IRN = IRN * KK
      RN = 0.5 + FLOAT(IRN) * 2.328306E-10
      KOUNT = KOUNT + 1
      IF (RN.GT.P(I)) GO TO 2300
      NS(I) = NS(I) + 1
      GO TO 2400
 2300 NF(I) = NF(I) +1
 2400 II = II + 1
      IF (II.LE.N(I)) GO TO 2200
      II = 1
      I = I + 1
      IF (I.LE.K) GO TO 2200
SIMULATION COMPLETE FOR REPLICATION J
COMPUTE M, V, ALPHA, AND BETA
      I = 1
```

```
      EXPU = 0.0
      VARU = 0.0
 2500 INC = 0
      IF (NF(I).EQ.0) GO TO 2700
 2600 S= NS(I) + INC
      EXPU = EXPU + 1.0/S
      VARU = VARU + 1.0 / (S*S)
      INC = INC + 1
      IF (NF(I).GT.INC) GO TO 2600
 2700 I = I + 1
      IF (I.LE.K) GO TO 2500
      IF(ICOMP2.EQ.0) GO TO 2730
COMPUTATION 2
      SUM2 = 0.0
      SUM3 = 0.0
      SUM4 = 0.0
      DO 2720 I= 1,K
      IF (NF(I).NE.0) GO TO 2720
      XNS1 = N(I) - 1
      SUM2 = SUM2 + 1.0/XNS1
      SUM3 = SUM3 + 1.0/(XNS1*XNS1)
      SUM4 = SUM4 + 1.0
 2720 CONTINUE
      D1 = 2.0 * SUM4 * SUM4
      IF (D1.EQ.0.0) GO TO 2730
      EXPU = EXPU + SUM2/D1
      VARU = VARU + SUM3/D1
 2730 IF(VARU.GT.0.0) GO TO 2800
      IF(ICOMP1.EQ.0) GO TO 2750
COMPUTATION 0
      NF1 = NF1 + 1
      EXPU = 1.0 / XNMAX1
      VARU = EXPU * EXPU
      BETA = XNMAX1
      ALPHA = 0.0
      TOBETA = 2.0 * BETA
      DF = 1.0
      GO TO 3200
COMPO WITH NO FAILURES
 2750 BETA = 0.0
      ALPHA = -1.0
      DF = 1.0
      CS = 0.0
      RSLCL(J) = 1.0
      GO TO 3300
 2800 BETA = EXPU / VARU
      TOBETA = 2.0 * BETA
      ALPHA = BETA * EXPU - 1.0
```

```
      DF = TOBETA * EXPU
      IF(DF.LE.100.0) GO TO 2870
      WRITE (6,2860) J, DF
 2860 FORMAT(1X, //, 'IN REP', I5, ', DF GT 100,  DF= ',F10.5,//)
      STOP
 2870 IF(DF.GE.1.0) GO TO 3200
      WRITE(6,2880) J, DF
 2880 FORMAT(1X, //, 12X, 'INREP', I5, ', DF LT 1.0, DF= ', F10.5,
     1'DF SET TO 1.0')
      DF = 1.0
SEARCH CHI SQUARE TABLE FOR CS
 3200 NDF = DF
      NDF1 = NDF + 1
      CS= (CSTABL(NDF1,L) - CSTABL(NDF,L)) * (DF-NDF) + CSTABL(NDF,L)
COMPUTE THE ESTIMATED SYSTEM RELIABILITY LCL RESULTING
FROM THIS SERIES OF SIMULATED TESTS
      RSLCL(J) = 1.0 / (2.7183 ** (CS/TOBETA))
      IF(RSLCL(J).LE.0.1) GO TO 3310
      IF(DF.LT.1.0) DF = 1.0
 3300 IF (IOUT.EQ.0 ) GO TO 3550
OUTPUT FROM REPLICATION
 3310 WRITE (6,3320) J
 3320 FORMAT (1X, ///, 11X, 'RESULTS OF REPLICATION', I5, //)
      WRITE (6,1100)
      ILOOP = 0
 3330 ILOOP = ILOOP + 1
      WRITE (6, 1300) ILOOP, P(ILOOP), N(ILOOP), NS(ILOOP), NF(ILOOP)
      IF (ILOOP.LT.K) GO TO 3330
      WRITE (6,3340) EXPU, VARU, ALPHA, BETA
 3340 FORMAT (1X, //, 16X, 'M= ', F10.5, /, 16X, 'V= ',
     1F10.5, /, 12X, 'ALPHA= ', F10.5, /, 13X, 'BETA= ', F10.5, /)
      WRITE (6,3400)
 3400 FORMAT (1X, /, 5X,'RESULTS USING BRAM APPROXIMATION',/)
      WRITE (6,3500) DF, CS,PCNTIL(L), RSLCL(J)
 3500 FORMAT (15X, 'DF= ', F10.5, /, 7X, 'CHI SQUARE= ', F10.5, //,
     112X, 'ESTIMATED ', F4.2,' LCL FOR SYSTEM RELIABILITY= ',F10.5,/)
 3550 IF (IPOI.EQ.0) GO TO 4100
ZERO OUT NS(I), NF(I), AND ADD N(I) TO NT(I)
 4100 DO 4200 I = 1, K
      NST(I) = NST(I) + NS(I)
      NFT(I) = NFT(I) + NF(I)
      NT(I) = NT(I) + N(I)
      NS(I) = 0
      NF(I) = 0
 4200 CONTINUE
      J = J + 1
      IF (J.LE.NREP) GO TO 2100
PRINT SUMMARY OF RANDOM NUMBER GENERATION AND TEST RESULTS
```

```
      WRITE (6,4300)                                                    00002390
 4300 FORMAT ('1', 17X, 'SUMMARY OF SIMULATION RESULTS',//)             00002400
      WRITE (6,4400) KOUNT, ISTART,IRN                                  00002410
 4400 FORMAT (1X,//, 12X,'NUMBER OF RANDOM NUMBERS GENERATED= ',        00002420
     1I10, /, 12X, 'RANDOM NUMBER GENERATOR SEED= ', I10, /,            00002430
     212X, 'LAST RANDOM NUMBER GENERATOR SEED= ', I15, /)               00002440
      WRITE (6,1100)                                                    00002450
      ILOOP = 0                                                         00002460
 4500 ILOOP = ILOOP + 1                                                 00002470
      WRITE (6,1300) ILOOP, P(ILOOP), NT(ILOOP), NST(ILOOP), NFT(ILOOP) 00002480
      IF (ILOOP.LT.K) GO TO 4500                                        00002490
      WRITE (6,4550) NF1                                                00002500
 4550 FORMAT (/, 12X, 'THERE WERE ' I5, ' REPLICATIONS WITH NO FAILURES 00002510
     1', /)                                                             00002520
      IF(IOUT.EQ.0) GO TO 5200                                          00002530
      WRITE (6, 4600)                                                   00002540
 4600 FORMAT (1X, ///, 12X, 'UNORDERED VALUES OF SYSTEM',               00002550
     1' RELIABILITY LCLS, READ LEFT TO RIGHT', /)                       00002560
 4800 KOUNT2 = 10                                                       00002570
      KOUNT3 = 1                                                        00002580
 4850 WRITE(6,4900) (RSLCL(J) , J= KOUNT3, KOUNT2)                      00002590
 4900 FORMAT(1X, 'BRAM', 7X, 10F10.5)                                   00002600
 5100 IF (KOUNT2.EQ.NREP)  GO TO 5200                                   00002610
      KOUNT2 = KOUNT2 + 10                                              00002620
      KOUNT3 = KOUNT3 + 10                                              00002630
      GO TO 4850                                                        00002640
ARRANGE THE SYSTEM RELIABILITY LCL VALUES IN ASCENDING ORDER            00002650
 5200 NR1 = NREP - 1                                                    00002660
      DO 5400 JJ = 1, NR1                                               00002670
      KR = NREP - JJ                                                    00002680
      KOUNT1 = 0                                                        00002690
      DO 5300 II = 1, KR                                                00002700
      IF (RSLCL(II).LE.RSLCL(II + 1)) GO TO 5300                        00002710
      KOUNT1 = KOUNT1 + 1                                               00002720
      TEMP = RSLCL(II)                                                  00002730
      RSLCL(II) = RSLCL(II + 1)                                         00002740
      RSLCL(II + 1) = TEMP                                              00002750
 5300 CONTINUE                                                          00002760
      IF (KOUNT1.EQ.0) GO TO 5450                                       00002770
 5400 CONTINUE                                                          00002780
FIND THE VALUE OF RSLCL WHICH IS THE (1-G)TH PERCENTILE                 00002790
OF ALL THE ORDERED VALUES                                               00002800
 5500 XNREP = NREP                                                      00002810
      J1 = PCNTIL(L) * XNREP                                            00002820
      RSLCL1 = RSLCL(J1)                                                00002830
FIND HOW MANY VALUES OF RSLCL(J) ARE .LE. TO RCOMP                      00002840
FROM THIS FIND THE TRUE LEVEL OF CONFIDENCE                             00002850
      DO 5600 JJ = 1, NREP                                              00002860
```

```
      IF (RSLCL(JJ).LT.RCOMP) GO TO 5600
      A(L) = JJ-1
      GO TO 5700
 5600 CONTINUE
 5700 CONF(L) = A(L) / XNREP
PRINT OUTPUT
      WRITE (6,5800)
 5800 FORMAT (1X, ///, 12X, 'ORDERED VALUES OF SYSTEM RELIABILITY',
     1 ' LCLS, READ LEFT TO RIGHT', /)
 5820 KOUNT2 = 10
      KOUNT3 = 1
 5830 WRITE (6,4900) (RSLCL(J), J= KOUNT3, KOUNT2)
      IF(IPOI.EQ.0) GO TO 5840
      WRITE (6,5000) (RSLPOI(J), J= KOUNT3, KOUNT2)
 5840 IF(KOUNT2.EQ.NREP)  GO TO 5850
      KOUNT2 = KOUNT2 + 10
      KOUNT3 = KOUNT3 + 10
      GO TO 5830
 5850 WRITE (6,3400)
      WRITE (6,5900) RCOMP
 5900 FORMAT (1X, //, 12X, 'SYSTEM RELIABILITY BY PRODUCT ',
     1'ASSUMPTION RULE= ', F10.5,/)
      WRITE (6,6000) PCNTIL(L), RSLCL1
 6000 FORMAT (12X, 'THE ', F5.2, ' PERCENTILE OF THE ORDERED VALUES ',
     1 'OF SYSTEM RELIABILITY LCL= ', F10.5, /)
      WRITE (6,6100) A(L), CONF(L)
 6100 FORMAT (12X, 'THERE WERE ', F6.2, ' VALUES OF RSLCL ',
     1 'LESS THAN OR EQUAL TO RCOMP', //, 12X,
     2 'THE TRUE LEVEL OF CONFIDENCE IS', F10.5)
      WRITE (6,6200)  TT
 6200 FORMAT (12X, 'TT= ', F10.3)
 6260 IF(L.GE.NGAMMA) GO TO 6300
      NF1 = 0
      L = L + 1
      GO TO 2000
 6300 IF (IFLAG2.NE.0) GO TO 6400
PREPARE FOR COMP1
      IRN = ISTART
      NF1 = 0
      ICOMP1 = 1
      ICOMP2 = 0
      IFLAG2 = 1
      GO TO 6500
 6400 IF (ISTOP.NE.0) GO TO 6700
PREPARE FOR COMP2
      IRN = ISTART
      ICOMP1 = 0
      ICOMP2 = 1
```

```
      NF1 = 0
       ISTOP = 1
ZERO OUT TOTALS
 6500 DO 6600 I= 1,K
      NST(I) = 0
      NFT(I) = 0
 6600 CONTINUE
      GO TO 1950
 6700 STOP
      END
INPUT DATA CARDS INCLUDE VALUES FOR K, NO. OF CONFIDENCE LEVELS TO
INVESTIGATE, NO. OF REPLICATIONS, CONFIDENCE LEVELS, COMPONENT
RELIABILITIES, NO. OF TESTS PER COMPONENT, AND A CHI SQUARE DISTRIBUTION
TABLE.
```

LIST OF REFERENCES

1. Center for Naval Analyses, O.E.G. Research Contribution No. 79, Confidence Limits for System Reliability, by Joseph Bram, 2 February 1968.

2. Borsting, Jack R., and Woods, W. Max, A Method for Computing Lower Confidence Limits on System Reliability Using Component Failure Data with Unequal Sample Sizes, Naval Postgraduate School, Monterey, California, June 1968.

INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Documentation Center Cameron Station Alexandria, Virginia 22314	2
2.	Library, Code 0212 Naval Postgraduate School Monterey, California 93940	2
3.	Professor W. M. Woods, Code 53Wo Department of Mathematics Naval Postgraduate School Monterey, California 93940	1
4.	Chief of Naval Personnel Pers 11b Department of the Navy Washington, D. C. 20370	1
5.	Naval Postgraduate School Department of Operations Research and Administrative Sciences Monterey, California 93940	1
6.	LT Samuel H. Evans, USN 1880 Carlisle Dr. San Marino, California 91108	1

DOCUMENT CONTROL DATA - R & D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1. ORIGINATING ACTIVITY *(Corporate author)* Naval Postgraduate School Monterey, California 93940	2a. REPORT SECURITY CLASSIFICATION Unclassified 2b. GROUP

3. REPORT TITLE

Evaluation of the Accuracy of a Lower Confidence Limit Estimate for Series System Reliability

4. DESCRIPTIVE NOTES *(Type of report and, inclusive dates)*

Master's Thesis; September 1972

5. AUTHOR(S) *(First name, middle initial, last name)*

Samuel Hall Evans

6. REPORT DATE September 1972	7a. TOTAL NO. OF PAGES 45	7b. NO. OF REFS 2
8a. CONTRACT OR GRANT NO. b. PROJECT NO. c. d.	9a. ORIGINATOR'S REPORT NUMBER(S) 9b. OTHER REPORT NO(S) *(Any other numbers that may be assigned this report)*	

10. DISTRIBUTION STATEMENT

Approved for public release; distribution unlimited.

11. SUPPLEMENTARY NOTES	12. SPONSORING MILITARY ACTIVITY Naval Postgraduate School Monterey, California 93940

13. ABSTRACT

The purpose of this study is to evaluate the accuracy of a procedure used to compute an estimate of the lower $100(1-\gamma)\%$ confidence limit for reliability of a system of independent components connected in logical series. The procedure takes a Bayesian approach and uses test data on the individual components where the sample sizes may be unequal and no knowledge of the component failure distribution is needed. A computer simulation is used to generate test failure data and to compute estimates for the lower $100(1-\gamma)\%$ confidence limit on system reliability.

14 KEY WORDS	LINK A		LINK B		LINK C	
	ROLE	WT	ROLE	WT	ROLE	WT
Reliability						
Bayesian						
Confidence Limit						

DD FORM 1 NOV 65 1473 (BACK)

S/N 0101-807-6821

JUL 31 1995

OCT 30

[illegible] 8 [illegible]

Thesis 139037
E779 Evans
c.1 Evaluation of the accuracy of a lower confidence limit estimate for series system reliability.

thesE779
Evaluation of the accuracy of a lower co
3 2768 000 98485 0
DUDLEY KNOX LIBRARY